Ai-M62-32S Specification

Version V1.0.0

Copyright ©2023

Copyright©2023 Shenzhen Ai-Thinker Technology Co., Ltd All Rights Reserved

Document resume

Version	Date	Develop/revise content	Edition	Approve
V1.0.0	2023.03.23	First Edition	NanNan Yuan	NingGuan

Copyright©2023 Shenzhen Ai-Thinker Technology Co., Ltd All Rights Reserved

Content

1. Product overview 4
1.1. Characteristics 5
2. Main parameters 6
2.1. Electrostatic requirements 6
2.2. Electrical characteristics 7
2.3. Wi-Fi radio frequency performance 7
2.4. BLE RF performance 8
2.5. Power consumption 8
3. Appearance size 9
4. Pin definition 10
5. Schematic diagram 13
6. Antenna parameters 14
6.1. Schematic of Antenna Test Prototype 14
6.2. Antenna s parameter 15
6.3. Antenna Gain and Efficiency 15
6.4. Antenna field pattern 16
7. Design guidance 17
7.1. Application guidance circuit 17
7.2. Recommended PCB package size 18
7.3. Antenna layout requirements 18
7.4. Power supply 19
7.5. GPIO 20
8. Storage conditions 21
9. Reflow Soldering Curve 21
10. Product packaging information 22
11. Contact us 22
Disclaimer and copyright notice 23
Notice 23

Copyright©2023 Shenzhen Ai-Thinker Technology Co., Ltd All Rights Reserved

2.4. BLE RF performance

Table 4 BLE RF Performance Table

Description	Typical value			Unit
Spectrum range	2400~2483.5MHz			MHz
Output power				
Mode	**Min.**	**Typical value**	**Max.**	**Unit**
1Mbps	-	10	15	dBm
2Mbps	-	10	15	dBm
Receiving sensitivity				
Mode	**Min.**	**Typical value**	**Max.**	**Unit**
1Mbps sensitivity @ 30.8%PER	-	-99	-	dBm
2Mbps sensitivity @ 30.8%PER	-	-97	-	dBm

2.5. Power consumption

The following power consumption data is based on a 3.3V power supply and measured at an ambient temperature of 25°C.

- The POUT power for all transmit modes is the measured value at the antenna interface.
- All transmission data are measured in the continuous transmission mode based on a duty cycle of 100%.

Table 5 Power consumption table

Mode	Min.	Average	Max.	Unit
Transmit 802.11B, 11Mbps,POUT = + 22dBm	-	423	-	mA
Transmit 802.11g, 54Mbps, POUT = + 19dBm	-	331	-	mA
Emission 802.11n, MCS7, POUT = + 19dBm	-	328	-	mA
Launch 802.11ax, MCS7, POUT = + 17dBm	-	293	-	mA
Receive 802.11B, packet length 1024 bytes	-	59	-	mA
Receive 802.11g, packet length 1024 bytes	-	59	-	mA
Receive 802.11n, packet length 1024 bytes	-	59	-	mA
Receive 802.11ax, packet length 1024 bytes	-	59	-	mA

Copyright©2023 Shenzhen Ai-Thinker Technology Co., Ltd All Rights Reserved

3. Appearance size

Front Front Back

Figure 3 appearance diagram (Rendering diagram is for reference only, subject to actual objects)



Front Back

Figure 4 dimension diagram

Copyright©2023 Shenzhen Ai-Thinker Technology Co., Ltd All Rights Reserved



Figure 5 screen printing representative information of shield

4. Pin definition

A total of 38 pins are connected to the Ai-M62-32S module, as shown in the pin diagram, the pin function definition table is an interface definition.



Figure 6 pin diagram

Copyright©2023 Shenzhen Ai-Thinker Technology Co., Ltd All Rights Reserved

Table 6 Pin Function Definition Table

Foot	Name	Functional description
1,15,38	GND	Grounding
2	VDD	3.3V power supply; The output current of external power supply is recommended to be above 500mA.
3	EN	Default as chip enable, high level valid
4,16,17,18,21,22,23,24,29,32,33,37	NC	NC is not available.
5	IO3	GPIO3/SPI_MOSI/I2S_DO/I2S_RCLK_O/I2C_SDA/ADC_CH3/PWM0
6	IO11/NC	Available by default, this IO port is shared with Flash in the module. If a module with external Flash is customized, the IO is not available. For use, please contact Ai-Thinker. GPIO11/SPI_MOSI/I2S_DO/I2S_RCLK_O/I2C_SDA/PWM0
7	IO12/NC	Available by default, this IO port is shared with Flash in the module. If a module with external Flash is customized, the IO is not available. For use, please contact Ai-Thinker.
8	IO1	GPIO1/SPI_SCLK/I2S_FS/I2C_SDA/ADC_CH8/PWM0
9	IO30	GPIO30/SPI_MISO/I2S_DI/I2S_RCLK_O/I2C_SCL/PWM0
10	IO0	GPIO0/SPI_SS/I2S_BCLK/I2C_SCL/ADC_CH9/PWM0
11	IO13/NC	Available by default, this IO port is shared with Flash in the module. If a module with external Flash is customized, the IO is not available. For use, please contact Ai-Thinker. GPIO13/SPI_SCLK/I2S_FS/I2C_SDA/ADC_CH5/PWM0
12	IO14/NC	Available by default, this IO port is shared with Flash in the module. If a module with external Flash is customized, the IO is not available. For use, please contact Ai-Thinker. GPIO14/SPI_MISO/I2S_DI/I2S_RCLK_O/I2C_SCL/ADC_CH4/PWM0
13	IO15/NC	Available by default, this IO port is shared with Flash in the module. If a module with external Flash is customized, the IO is not available. For use, please contact Ai-Thinker. GPIO15/SPI_MOSI/I2S_DO/I2S_RCLK_O/I2C_SDA/PWM0

Copyright©2023 Shenzhen Ai-Thinker Technology Co., Ltd All Rights Reserved

14	IO16/NC	Available by default, the IO port is shared with the PIN pin of the 32.768KHz crystal oscillator input inside the module. If the module of the internal patch 32.768KHz crystal oscillator is customized, the IO is in NC state. GPIO16/SPI_SS/I2S_BCLK/I2C_SCL/XTAL_32K_IN/PWM0
19	DP	USB_DP
20	DM	USB_DM
25	IO2/NC	The default NC is not available. If you need to use it, please contact Ai-Thinker. If elicited, support Bootstrap/GPIO2/SPI_MISO/I2S_DI/I2S_RCLK_O/I2C_SCL/ADC_CH2/PWM0
26	IO10/NC	Available by default, this IO port is shared with Flash in the module. If a module with external Flash is customized, the IO is not available. For use, please contact Ai-Thinker. GPIO10/SPI_MISO/I2S_DI/I2S_RCLK_O/I2C_SCL/ADC_CH7/PWM0
27	IO28	GPIO28/SPI_SS/I2S_BCLK/I2C_SCL/ADC_CH11/PWM0
28	IO17/NC	Available by default, the IO port is shared with the 32.768KHz crystal output PIN pin inside the module. If the module of the internal patch 32.768KHz crystal oscillator is customized, the IO is in NC state. GPIO17/SPI_SCLK/I2S_FS/I2C_SDA/XTAL_32K_OUT/PWM0
30	IO27	GPIO27/SPI_MOSI/I2S_DO/I2S_RCLK_O/I2C_SDA/ADC_CH10/PWM0
31	IO29	GPIO29/SPI_SCLK/I2S_FS/I2C_SDA/PWM0
34	RXD	RXD/GPIO22/SPI_MISO/I2S_DI/I2S_RCLK_O/I2C_SCL/PWM0
35	TXD	TXD/GPIO21/SPI_SCLK/I2S_FS/I2C_SDA/ADC_RCAL_VOUT/PWM0
36	IO20	GPIO20/SPI_SS/I2S_BCLK/I2C_SCL/ADC_CH0/PWM0
Note: 1. GPIO2 is used as a Bootstrap. When the power-on moment is high, the module enters the burning mode. When the power-on moment is low, the module starts normally.		

Copyright©2023 Shenzhen Ai-Thinker Technology Co., Ltd All Rights Reserved

5. Schematic diagram



Figure 7 Schematic Diagram

Copyright©2023 Shenzhen Ai-Thinker Technology Co., Ltd All Rights Reserved

6. Antenna parameters

6.1. Schematic of Antenna Test Prototype



Figure 8 schematic diagram of antenna test prototype

Copyright©2023 Shenzhen Ai-Thinker Technology Co., Ltd All Rights Reserved

6.2. Antenna s parameter



Figure 9 antenna s parameters

6.3. Antenna Gain and Efficiency

Table 7 Antenna Gain and Efficiency

Frequency ID	1	2	3	4	5	6	7	8	9	10	11
Frequency(MHz)	2400	2410	2420	2430	2440	2450	2460	2470	2480	2490	2500
Gain (dBi)	1.04	1.26	1.42	1.52	1.67	1.76	1.89	1.90	1.50	1.40	1.30
Efficiency (%)	53.34	55.78	57.93	59.05	60.96	62.73	63.90	63.74	60.33	59.98	57.86

Copyright©2023 Shenzhen Ai-Thinker Technology Co., Ltd All Rights Reserved

6.4. Antenna field pattern



Figure 10 antenna field diagram

Copyright©2023 Shenzhen Ai-Thinker Technology Co., Ltd All Rights Reserved

7. Design guidance

7.1. Application guidance circuit



Figure 11 Application Guidance Circuit

- IO2 is the module start control pin, which is in normal working mode at low level and in firmware burning mode at high level. The default low level inside the chip.
- GPIO2/NC, not available by default
- GPIO10/GPIO11/GPIO12/GPIO13/GPIO14/GPIO15, available by default. These IO ports are shared with the internal Flash of the module. If the module with external Flash is customized, it cannot be used. For use, please contact Ai-Thinker.
- GPIO16/GPIO17, available by default. These IO ports are shared with the PIN pin of the 32.768KHz crystal oscillator inside the module. If the module of the internal patch 32.768KHz crystal oscillator is customized, the IO is in NC state.

Copyright©2023 Shenzhen Ai-Thinker Technology Co., Ltd All Rights Reserved

7.2. Recommended PCB package size



Figure 12 Recommended PCB Package Size

7.3. Antenna layout requirements

- In the installation position on the motherboard, the following 2 methods are recommended:

Scheme 1: Place the module on the edge of the main board, and the antenna area extends out of the edge of the main board.

Scheme 2: Place the module on the edge of the motherboard, and the edge of the motherboard hollowed out an area at the antenna position.

- In order to meet the performance of the on-board antenna, it is forbidden to place metal parts around the antenna, away from high-frequency devices.

Copyright©2023 Shenzhen Ai-Thinker Technology Co., Ltd All Rights Reserved



Figure 13 schematic diagram of antenna layout

7.4. Power supply

- Recommended 3.3V voltage, peak current above 500mA.
- LDO is recommended for power supply; If DC-DC is used, it is recommended that the ripple be controlled within 30mV.
- The DC-DC power supply circuit suggests to reserve the position of the dynamic response capacitor, which can optimize the output ripple when the load changes greatly.
- It is recommended to add ESD devices to the 3.3V power interface.



Figure 14 DC-DC step-down circuit diagram

Copyright©2023 Shenzhen Ai-Thinker Technology Co., Ltd All Rights Reserved

7.5. GPIO

- Some IO ports are led out from the periphery of the module. If you need to use a resistor of 10-100 ohms in series on the IO port. This can suppress overshoot and make the level on both sides more stable. It is helpful for both EMI and ESD.
- For the up and down of the special IO port, please refer to the instructions in the specification, which will affect the startup configuration of the module.
- The IO port of the module is 3.3V. If the level of the IO port of the main control and the module does not match, a level conversion circuit needs to be added.
- If the IO port is directly connected to the peripheral interface or terminals such as pins, it is recommended to reserve ESD devices at the IO port wiring close to the terminals.



Figure 15 Level Shift Circuit

Copyright©2023 Shenzhen Ai-Thinker Technology Co., Ltd All Rights Reserved

8. Storage conditions

The product sealed in the moisture-proof bag should be stored in a non-condensing atmospheric environment of <40° C/90%RH.

The moisture sensitivity level MSL of the module is level 3.

After the vacuum bag is unpacked, it must be used within 168 hours at 25±5 ℃/60%RH, otherwise it needs to be baked before it can be put on line again.

9. Reflow Soldering Curve



Figure 16 reflow soldering graph

Copyright©2023 Shenzhen Ai-Thinker Technology Co., Ltd All Rights Reserved

10.Product packaging information

The Ai-M62-32S module is packaged with braided tape, 800 pcs/disk. As shown in the following figure:

Figure 17 packing tape drawing

11.Contact us

Ai-Thinker official website　Office forum　Develop DOCS

LinkedIn　Tmall shop　Taobao shop　Alibaba shop

Technical support email：support@aithinker.com

Domestic business cooperation：sales@aithinker.com

Overseas business cooperation：overseas@aithinker.com

Company Address：Room 403,408-410, Block C, Huafeng Smart Innovation Port, Gushu 2nd Road, Xixiang, Baoan District, Shenzhen.

Tel：+86-0755-29162996

WeChat mini program

WeChat official account

Copyright©2023 Shenzhen Ai-Thinker Technology Co., Ltd All Rights Reserved

Disclaimer and copyright notice

The information in this article,including the URL address for reference,is subject to change without notice.

The document is provided"as is"without any guarantee responsibility,including any guarantee for merchantability,suitability for a specific purpose,or non-infringement,and any guarantee mentioned elsewhere in any proposal,specification or sample.This document does not bear any responsibility,including the responsibility for infringement of any patent rights arising from the use of the information in this document.This document does not grant any license for the use of intellectual property rights in estoppel or other ways,whether express or implied.

The test data obtained in the article are all obtained from Ai-Thinker's laboratory tests,and the actual results may vary slightly.

All brand names,trademarks and registered trademarks mentioned in this article are the property of their respective owners,and it is hereby declared.

The final interpretation right belongs to Shenzhen Ai-Thinker Technology Co.,Ltd.

Notice

Due to product version upgrades or other reasons,the contents of this manual may be changed.

Shenzhen Ai-Thinker Technology Co.,Ltd.reserves the right to modify the contents of this manual without any notice or prompt.

This manual is only used as a guide.Shenzhen Ai-Thinker Technology Co.,Ltd. makes every effort to provide accurate information in this manual.However, Shenzhen Ai-Thinker Technology Co.,Ltd. does not guarantee that the contents of the manual are completely free of errors.All statements and information in this manual And the suggestion does not constitute any express or implied guarantee.

Copyright©2023 Shenzhen Ai-Thinker Technology Co., Ltd All Rights Reserved